#### ESC 80 EMERGENCY EXIT LIGHT TWS8092WAT

































We reserve the rights to make modifications without notice.









# Self-contained ESCAP Emergency Exit Light with 1 h Super Capacitor and Wireless Central Monitoring

ESC 80 is an emergency exit light equipped with a light plate, combining cutting edge technology combined with modern luminaire design. Thanks to Teknoware's innovative electronics and product design, the ESC 80 luminaire combines uniformly illuminated pictograms, low power consumption, as well as a slender appearance.

There is a selection of three different luminaire sizes. ESC 80 luminaires can be used as 1 or 2 sided, as well as recess or surface mounted.

ESC 80 is particularly easy and fast to install thanks to a separate mounting piece, into which

Copyright © 2024 Teknoware. All rights reserved.

Date: May 18, 2024 | Source: teknoware.fi/en/our-solutions/emergency-lightingbuildings/esc-80-emergency-exit-light-tws8092wat



also the power supply is connected.



| Product Code                        | TWS8092WAT                      |  |
|-------------------------------------|---------------------------------|--|
| Feature                             | Aalto Control, Escap, Lumi Test |  |
| Mounting (standard)                 | wall, ceiling                   |  |
| Mounting (optional)                 | recess, flag, pendel            |  |
| Customs Code                        | 94056080                        |  |
| GTIN Code                           | 06438045028385                  |  |
| ETIM Product Class                  | EC001957                        |  |
| Length                              | 268 mm                          |  |
| Width                               | 40 mm                           |  |
| Height                              | 185 mm                          |  |
| Weight                              | 0,74 kg                         |  |
| Backup                              | 1h                              |  |
| Max Input Power VA                  | 4 VA                            |  |
| Nominal Supply Voltage              | 220-240 V, 50/60 Hz AC          |  |
| Protection Class                    | II                              |  |
| IP Class                            | IP44                            |  |
| Temperature Range Min - Max         | -25+35 °C                       |  |
| Glow Wire Test of Plastic Materials | 850 °C                          |  |
| Viewing Distance                    | 20/26/30 m                      |  |
| Light Source                        | LED                             |  |
| Body Material                       | plastic                         |  |
| Aperture for Recess Mounting        | 45 x 275 mm                     |  |
| Colour                              | RAL9005                         |  |
| Electrical Installation             | 2/3 x 2,5 mm <sup>2</sup>       |  |

# ONE OR MORE OF THESE IS ALSO REQUIRED:

## PICTOGRAMS FOR EMERGENCY EXIT





#### LIGHTS

| Product Code | Pictogram      | Viewing Distance (m) | Compatible Product Groups    |
|--------------|----------------|----------------------|------------------------------|
| PBV80202E    | 42 V2          | 20                   | ESC 80 Emergency Exit Lights |
| PBV80202E3   | <b>₹ •</b>     | 20                   | ESC 80 Emergency Exit Lights |
| PBV80201E    | 3 → € 2        | 20                   | ESC 80 Emergency Exit Lights |
| PBV80201E1   | <b>₽</b> →     | 20                   | ESC 80 Emergency Exit Lights |
| PBV80201E2   | ← 🔁            | 20                   | ESC 80 Emergency Exit Lights |
| PBV80262E    | <b>₹ ₹ ₹ ₹</b> | 26                   | ESC 80 Emergency Exit Lights |
| PBV80262E3   | <b>₹ •</b>     | 26                   | ESC 80 Emergency Exit Lights |
| PBV80261E    | 5 → 5          | 26                   | ESC 80 Emergency Exit Lights |
| PBV80261E1   | <b>₽</b> →     | 26                   | ESC 80 Emergency Exit Lights |
| PBV80261E2   | ← 52           | 26                   | ESC 80 Emergency Exit Lights |
| PBV80302E    | <b>5 4 5 4</b> | 30                   | ESC 80 Emergency Exit Lights |
| PBV80302E3   | <b>₽</b>       | 30                   | ESC 80 Emergency Exit Lights |
| PBV80301E    | 5 → 5          | 30                   | ESC 80 Emergency Exit Lights |
| PBV80301E1   | <b>₽</b> →     | 30                   | ESC 80 Emergency Exit Lights |
| PBV80301E2   | ← 🔁            | 30                   | ESC 80 Emergency Exit Lights |

## **OPTIONAL ACCESSORIES:**

# SHOCK PROTECTING COVERS FOR EMERGENCY LIGHTS



| Product Code | Product Name                    | Compatible Product Groups                                  |
|--------------|---------------------------------|------------------------------------------------------------|
| TW77507B     | Shock protecting cover TW77507B | ESC 10 Emergency Exit Lights, ESC 80 Emergency Exit Lights |

# COVER LABELS FOR EMERGENCY EXIT







## **LIGHTS**

| Product Code | Pictogram | Compatible Product Groups    |
|--------------|-----------|------------------------------|
| XWT8003      |           | ESC 80 Emergency Exit Lights |
| XWT8002      |           | ESC 80 Emergency Exit Lights |
| XWT8005      |           | ESC 80 Emergency Exit Lights |







