


ESC 81 LED EMERGENCY EXIT LIGHT TWS8192WMT



Self-contained ESCAP Emergency Exit Light with 1 h Super Capacitor and Lumi Test Self-testing

ESC 81 is an innovative exit light equipped with a light plate. It combines cutting edge technology with modern luminaire design.

Evenly illuminated light plates, low power consumption and slender looking luminaires are the result of Teknoware's pioneering, expertise in electronics and product design. Luminaire can be used as 1 or 2 sided, recess and surface mounted.

ESC 81 is particularly easy and fast to install thanks to a separate mounting piece, into which also the power supply is connected.

We reserve the rights to make modifications without notice.
Copyright © 2024 Teknoware. All rights reserved.
Date: May 20, 2024 | Source: [teknoware.fi/en/our-solutions/emergency-lighting-buildings/esc-81-led-emergency-exit-light-tws8192wmt](https://www.teknoware.fi/en/our-solutions/emergency-lighting-buildings/esc-81-led-emergency-exit-light-tws8192wmt)

Teknoware Oy | P.O. Box 19, 15101 Lahti | Ilmarisentie 8, 15200 Lahti Finland
Tel +358 3 883 020 | VAT-number FI01494751 | [teknoware.com](https://www.teknoware.com) | emexit@teknoware.com



Product Code	TWS8192WMT
Feature	Escap, Lumi Test
Mounting (standard)	ceiling, wall
Mounting (optional)	recess, flag, pendel
Customs Code	94056080
GTIN Code	06438045028439
ETIM Product Class	EC001957
Length	405 mm
Width	40 mm
Height	287 mm
Weight	1,4 kg
Backup	1 h
Max Input Power VA	4 VA
Nominal Supply Voltage	220-240 V, 50/60 Hz AC
Protection Class	II
IP Class	IP44
Temperature Range Min - Max	-25...+35 °C
Glow Wire Test of Plastic Materials	850 °C
Viewing Distance	40/60 m
Light Source	LED
Body Material	plastic
Aperture for Recess Mounting	53 x 415 mm
Colour	RAL9005
Electrical Installation	2/3 x 2,5 mm ²

ONE OR MORE OF THESE IS ALSO REQUIRED:

PICTOGRAMS FOR EMERGENCY EXIT












We reserve the rights to make modifications without notice.
 Copyright © 2024 Teknoware. All rights reserved.
 Date: May 20, 2024 | Source: teknoware.fi/en/our-solutions/emergency-lighting-buildings/esc-81-led-emergency-exit-light-tws8192wmt



Teknoware Oy | P.O. Box 19, 15101 Lahti | Ilmarisentie 8, 15200 Lahti Finland
 Tel +358 3 883 020 | VAT-number FI01494751 | teknoware.com | emexit@teknoware.com

LIGHTS


Product Code	Pictogram	Viewing Distance (m)	Compatible Product Groups
PBV81402E		40	ESC 81 Emergency Exit Lights
PBV81402E3		40	ESC 81 Emergency Exit Lights
PBV81401E		40	ESC 81 Emergency Exit Lights
PBV81401E1		40	ESC 81 Emergency Exit Lights
PBV81401E2		40	ESC 81 Emergency Exit Lights
PBV81602E		60	ESC 81 Emergency Exit Lights
PBV81601E		60	ESC 81 Emergency Exit Lights
PBV81601E1		60	ESC 81 Emergency Exit Lights
PBV81601E2		60	ESC 81 Emergency Exit Lights

OPTIONAL ACCESSORIES:

SHOCK PROTECTING COVERS FOR EMERGENCY LIGHTS



Product Code	Product Name	Compatible Product Groups
TW77510B	Shock protecting cover TW77510B	ESC 10 Emergency Exit Lights, DISCONTINUED: ESC 6L Emergency Exit Lights, ESC 29 Emergency Exit Lights, Safe 29 Emergency Lights, ESC 81 Emergency Exit Lights



We reserve the rights to make modifications without notice.

Copyright © 2024 Teknoware. All rights reserved.

Date: May 20, 2024 | Source: teknoware.fi/en/our-solutions/emergency-lighting-buildings/esc-81-led-emergency-exit-light-tws8192wmt

Teknoware Oy | P.O. Box 19, 15101 Lahti | Ilmarisentie 8, 15200 Lahti Finland
Tel +358 3 883 020 | VAT-number FI01494751 | teknoware.com | emexit@teknoware.com

